




**T-3 1/4****MINIATURE LAMPS****Applications:  
Indicator  
Radio****Aircraft  
Auto**

LINE NO.	DESIGN		M.S.C.P. (APPROX.)	LIFE (HRS.)	FILAMENT SHAPE	WEDGE BASE	MINIATURE BAYONET BASE	MINIATURE SCREW BASE
	VOLTS	AMPS						
1	2.00	.06	.02	1000	C-6		PE 1809	
2	2.47	.25	.45	30	C-2R	PE 127		
3	2.50	.50	.50	3000	C-2R		PE 43	PE 41
4	3.20	.35	.50	3000	C-2R		PE 45	PE 42
5	3.20	.16	.20	3000	C-2R		PE 1450	
6	3.75	.09	.18	1000	C-2R		PE 1688	
7	4.00	.08	.07	1000	S-2		PE 1804	
8	4.00	.08	.06	2000	C-6		PE 1867	
9	5.00	.09	.25	1500	C-2R	PE 285	PE 1850	
10	5.00	.07	.19	1500	C-6	PE 740		
11	5.00	.12	.40	40	C-2R		PE 1851	
12	5.00	.07	.19	1000	C-6		PE 1906	
13	6.00	.70	3.40	500	C-2R		PE 316	
14	6.00	.14	.35	2000	C-2V	PE 820	PE 1689	
15	6.30	.25	.90	3000	C-2R	PE 444	PE 44	PE 46
16	6.30	.15	.50	3000	C-2R		PE 47	PE 40
17	6.30	.50	2.00	2000	C-2R		PE 238	
18	6.30	.36	.67	5000	C-2R		PE 239	
19	6.30	.36	.67	5000	C-2R		PE 240	
20	6.30	.15	.33	5000	C-2R	PE159	PE 267	
21	6.30	.15	.33	20000	C-2R		PE 755	
22	6.30	.04	.08	5000	C-6		PE 1302	
23	6.30	.40	1.40	3000	C-2R		PE 1810	
24	6.30	.15	.38	5000	C-2R		PE 1847	
25	6.30	.25	.65	5000	C-2R	PE 259	PE 1866	
26	6.30	.15	.52	1500	C-2V	PE 447		
27	7.00	.43	2.00	1500	C-2R	PE 147		
28	7.00	.34	.30	25000	C-2F	PE 190		
29	7.00	.50	2.00	1500	C-2R		PE 1838	
30	7.00	.19	.30	2000	C-2R		PE 1908	
31	9.84	.50	4.00	200	C-2R	PE 947		
32	10.00	.13	.85	250	C-2V	PE 280		
33	12.00	.42	2.60	1000	C-2R	PE 3-501		
34	12.00	.25	1.11	4000	C-2V	PE 3-504		
35	12.00	.17	.80	4000	C-2V	PE 3-509		
36	13.00	.33	3.00	1000	C-2V	PE 192	PE 1816	
37	14.00	.27	1.50	5000	C-2F	PE 124		
38	14.00	.24	2.00	500	C-2V	PE 158	PE 1894	
39	14.00	.19	1.00	1500	C-2F	PE 161		
40	14.00	.35	3.00	1500	C-2F	PE 168		
41	14.00	.33	2.00	5000	C-2F	PE 193		
42	14.00	.27	2.00	1500	C-2F	PE 194		
43	14.00	.08	.31	15000	C-2F	PE 658	PE 756	
44	14.40	.24	1.00	5000	C-2F	PE 184	PE 216	