


T-31/4

MINIATURE LAMPS

Applications:
Indicator
Radio

Aircraft
Auto



LINE NO.	DESIGN		M.S.C.P. (APPROX.)	LIFE (HRS.)	FILAMENT SHAPE	WEDGE BASE	MINIATURE BAYONET BASE	MINIATURE SCREW BASE
	VOLTS	AMPS						
1	14.00	.15	1.50	200	C-2V		PE 1488	PE 1491
2	14.00	.20	1.40	3000	C-2V		PE 1815	PE 1497
3	14.00	.41	3.00	1500	C-2F		PE 181	
4	14.00	.27	2.00	1500	C-2F		PE 1889	
5	14.00	.24	2.00	500	C-2F		PE 1891	
6	14.00	.33	2.00	7500	C-2F		PE 1893	
7	14.40	.10	.86	1000	C-2V		PE 1813	
8	14.40	.12	.75	1000	C-2F		PE 1892	
9	14.40	.10	.86	1000	C-2V		PE 1909	
10	15.50	.24	2.20	500	C-2F		PE 1881	
11	18.00	.15	1.80	250	C-2V		PE 1826	
12	24.00	.06	.90	20	C-2F		PE 1437	
13	24.00	.17	3.30	250	C-2V		PE 1818	
14	24.00	.13	1.00	5000	C-2F	PE 3-505		
15	24.00	.02	2.40	5000	C-2F	PE 3-507		
16	28.00	.07	.85	10000	C-2F	PE 152		
17	28.00	.10	1.60	1000	C-2V	PE 400		
18	28.00	.17	3.00	1500	C-2F	PE 464	PE 1864	
19	28.00	.04	.30	7000	C-2F	PE 585		
20	28.00	.20	3.00	7000	C-2F	PE 655	PE 1873	
21	28.00	.06	.62	2500	C-2F	PE 656		
22	28.00	.08	.62	7500	C-2F	PE 657	PE 757	
23	28.00	.17	3.40	500	C-2F		PE 313	PE 1821
24	28.00	.04	.34	2500	C-2F		PE 1819	
25	28.00	.10	1.60	1000	C-2F		PE 1820	
26	28.00	.07	1.00	1000	C-2F		PE 1829	
27	28.00	.02	.20	3000	C-2F		PE 1843	
28	36.00	.10	2.10	1000	C-2F		PE 1822	
29	37.50	.05	.65	3000	C-2F		PE 1828	PE 1832
30	48.00	.10	3.20	1000	C-2F		PE 1823	
31	55.00	.05	.72	7500	C-2F			PE 750
32	55.00	.05	1.10	5000	C-2F		PE 1835	

All dimensions are in mm