

T-2 1/2

MINIATURE LAMPS

Applications:
Pilot



LINE NO.	DESIGN		M.S.C.P. (APPROX.)	LIFE (HRS.)	FILAMENT SHAPE	WIRE TERMINAL	MINIATURE BAYONET BASE
	VOLTS	AMPS					
1	6.0	.14	.12	20000	C-2F		PE 6MB
2	12.0	.17	.35	12000	C-2F		PE 12MB
3	24.0	.07	.50	10000	C-2F		PE 24MB
4	28.0	.04	.29	5000	C-2F		PE 28MB
5	48.0	.05	-	10000	CC-2F		PE 48MB
6	60.0	.05	.73	7500	CC-2F		PE 60MB
7	90.0	.03	.37	5000	CC-3A		PE 90MB
8	120.0	.025	.36	10000	CC-3A		PE 120MB
9	120.0	.052	1.43	3000	CC-3A		PE 120MB/6
10	120.0	.052	1.43	3000	CC-3A	PE 120PS/6	
11	155.0	.025	.20	10000	CC-3A		PE 155MB