




T-2

## MINIATURE LAMPS

Applications:  
Indicator  
Switchboard

Pilot



LINE NO.	DESIGN		M.S.C.P. (APPROX.)	LIFE (HRS.)	FILAMENT SHAPE	SLIDE NO.6 BASE	SLIDE NO.6 BASE	SLIDE NO.3 BASE
	VOLTS	AMPS						
1	4.0	.190	450	5000	C-2V			PE 4A
2	6.0	.040	180	4000	C-2V			PE 6C
3	6.0	.140	510	15000	C-2V			PE 6A
4	6.0	.240	1580	5000	C-2V	PE 53B	PE 51B	
5	6.0	.290	270	15000	C-2F			PE 6B
6	8.0	.090	600	1000	C-2V			PE 8A
7	10.0	.035	100	10000	C-6			PE 10EX
8	10.0	.035	-	10000	C-6			PE 10X
9	10.0	.035	275	10000	C-6	PE 53A	PE 51A	
10	10.0	.110	600	5000	C-2V			PE 10A
11	10.0	.250	900	5000	C-2F			PE 10B
12	12.0	.035	650	2000	C-2V			PE 12B
13	12.0	.040	650	7500	C-2V		PE 12ESB/6	
14	12.0	.100	1200	8000	C-2F			PE 12A
15	12.0	.170	1500	5000	C-2V			PE 12C
16	15.0	.100	720	1000	C-2F			PE 15A
17	18.0	.100	720	5000	C-2F			PE 16E
18	18.0	.040	800	1000	C-2F			PE 18A
19	18.0	.100	600	10000	C-2F			PE 18B
20	24.0	.020	100	10000	C-2F			PE 24H
21	24.0	.030	600	1000	C-2F			PE 24A
22	24.0	.030	430	8000	C-2F		PE 52A	
23	24.0	.035	600	7000	C-2F			PE 24E
24	24.0	.040	1000	4000	C-2F			PE 24B
25	24.0	.072	1400	6000	C-2F			PE 24C
26	24.0	.090	1120	7000	C-2F			PE 24F
27	24.0	.100	1500	5000	C-2F			PE 24D
28	30.0	.038	1000	4000	C-2F			PE 30C
29	30.0	.038	1500	3000	C-2F			PE 30X
30	30.0	.072	2000	3000	CC-2F			PE 30A
31	30.0	.100	3000	4000	CC-2F			PE 30B
32	32.0	.040	1600	3500	C-2F			PE 32B
33	35.0	.040	1000	7500	C-2F			PE 35A
34	35.0	.072	700	5000	CC-2F			PE 35B
35	35.0	.100	750	5000	CC-2F			PE 35C
36	40.0	.072	480	5000	CC-2F			PE 40A
37	48.0	.021	100	20000	CC-2F			PE 48D
38	48.0	.035	400	7000	CC-2F			PE 48C
39	48.0	.045	1000	5000	CC-2F			PE 48H
40	48.0	.052	800	5000	CC-2F			PE 48G
41	48.0	.072	2000	5000	CC-2F			PE 48A
42	55.0	.050	1400	5000	CC-2F			PE 55C
43	60.0	.050	1600	5000	CC-2F			PE 60A

All dimensions are in mm.